

Small frequency approximation of (causal) dissipative pressure waves

R. Kowar*

* *Department of Mathematics, University of Innsbruck,
Technikerstrasse 21a/2, A-6020, Innsbruck, Austria
(e-mail: richard.kowar@uibk.ac.at)*

Abstract:

In this paper we discuss the problem of small frequency approximation of the causal dissipative pressure wave model proposed in Kowar et al. (2010). We show that for appropriate situations the Green function G^c of the causal wave model can be approximated by a noncausal Green function G_M^{pl} that has frequencies only in the small frequency range $[-M, M]$ ($M \leq 1/\tau_0$, τ_0 relaxation time) and obeys a power law. For such cases, the noncausal wave G_M^{pl} contains partial waves propagating arbitrarily fast but the sum of the noncausal waves is small in the L^2 -sense.

Keywords: Attenuation, Dispersion, Wave equations, Causality

1. INTRODUCTION: FREQUENCY FRAMEWORK

In the first section we summarize the general framework of frequency driven wave dissipation.

From the mathematical point of view, in case of a *homogeneous* and *isotropic* medium, dissipative pressure waves can be modeled by (cf. e.g. Kowar et al. (2010))

$$p(\mathbf{x}, t) = (G *_{\mathbf{x}, t} f)(\mathbf{x}, t) \quad \mathbf{x} \in \mathbb{R}^3, t \in \mathbb{R}$$

with

$$p(\cdot, t) = 0 \quad \text{and} \quad \frac{\partial p}{\partial t}(\cdot, t) = 0 \quad \text{for} \quad t < 0, \quad (1)$$

where G denotes a *distribution (Green function)*, $*_{\mathbf{x}, t}$ denotes the space-time convolution and f denotes a *forcing term (source term)* which models wave generation. We note that f is the same forcing term as in the absence of dissipation as long as (1) holds. (This is not true if $p(\mathbf{x}, t)$ is calculated for $t \geq t_0$ ($t_0 > 0$) from initial data at t_0 .)

1.1 The Green function

The Green function can be modeled by

$$\hat{G}(\mathbf{x}, \omega) = \frac{e^{-\beta_*(|\mathbf{x}|, \omega)}}{4\pi|\mathbf{x}|} e^{i\frac{\omega}{c_0}|\mathbf{x}|} \quad \mathbf{x} \in \mathbb{R}^3, \omega \in \mathbb{R}, \quad (2)$$

where $\Re(\beta_*(|\mathbf{x}|, \omega)) > 0$ is even in ω and $\Im(\beta_*(|\mathbf{x}|, \omega))$ is odd in ω . Here $\hat{G}(\mathbf{x}, \omega)$ denotes the Fourier transform of $G(\mathbf{x}, t)$ with respect to time t . The last two conditions guarantee that $G(\mathbf{x}, t)$ is real-valued. We focus on the cases

$$\beta_*(\mathbf{x}, \omega) = \alpha_*(\omega) |\mathbf{x}|. \quad (3)$$

We call $\alpha_* = \alpha_*(\omega)$ and $\alpha = \Re(\alpha_*(\omega))$ the *attenuation-dispersion law* and the *attenuation law*, respectively.

1.2 The wave equation

The above dissipative wave model satisfies the following *integro-differential equation*

$$\nabla^2 p(\mathbf{x}, t) - \left(D_* + \frac{1}{c_0} \frac{\partial p}{\partial t} \right)^2 p(\mathbf{x}, t) = -f(\mathbf{x}, t), \quad (4)$$

where D_* denotes the time convolution operator

$$\mathcal{F}\{D_*(g)\}(\omega) = \frac{1}{\sqrt{2\pi}} \alpha_*(\omega) \mathcal{F}\{g\}(\omega)$$

defined for appropriate functions $g = g(t)$. Here $\mathcal{F}\{g\}$ denotes the Fourier transform of g with respect to time.

More details about attenuation-dispersion laws and respective wave equations can be found in e.g. Nachman et al. (1990), Szabo (1995), Waters et al. (2000), Chen et al. (2004), Patch et al. (2006), Kelly et al. (2008) and Kowar et al. (2012).

2. ATTENUATION-DISPERSION LAWS AND CAUSALITY

2.1 What do we mean by causality?

Let $c_F < \infty$ denote the (constant) speed of the wave front of the wave G . Causality requires that *the wave front initiated at the origin $\mathbf{0}$ at time $t = 0$ arrives at position $\mathbf{x} \neq \mathbf{0}$ not before the time period $T(|\mathbf{x}|) = \frac{|\mathbf{x}|}{c_F}$ is over*. Mathematically this is equivalent to the following *causality condition*: for each $c_1 \geq c_F$ we have

$$G\left(\mathbf{x}, t + \frac{|\mathbf{x}|}{c_1}\right) = 0 \quad \text{if} \quad t < 0 \quad \text{and} \quad |\mathbf{x}| \neq 0. \quad (5)$$

Various dissipative wave models are analysed with respect to causality in Kowar et al. (2012). In particular, it is shown that (3) implies $c_F = \text{const.}$ if $c_F < \infty$. See also Kelly et al. (2008).

2.2 Attenuation-dispersion laws ($\gamma \in (1, 2]$)

In this paper we consider the *attenuation-dispersion laws*

$$\alpha_*^c(\omega) = \frac{\alpha_1(-i\omega)}{c_0 \sqrt{1 + (-i\tau_0\omega)^{\gamma-1}}} \quad (6)$$

and

$$\alpha_*^{pl}(\omega) = a_1 \frac{(-i\omega)^\gamma}{\cos(\gamma\pi/2)} + a_2(-i\omega) \quad (7)$$

for $\omega \in \mathbb{R}$ with $\gamma \in (1, 2]$, $c_0 \in (0, \infty)$ and $\alpha_1, \tau_0, a_1 > 0$. $\alpha_*^{pl} = \alpha_*^{pl}(\omega)$ is called the *frequency power law*.

Let

$$a_1 = \frac{\alpha_1 \tau_0^{\gamma-1}}{2 c_0} |\cos(\gamma\pi/2)| \quad \text{and} \quad a_2 = \frac{\alpha_1}{c_0}, \quad (8)$$

then it follows from

$$(-i\omega)^\gamma = |\omega|^\gamma \left\{ \cos\left(\gamma\frac{\pi}{2}\right) - i \sin\left(\gamma\frac{\pi}{2}\right) \text{sgn}(\omega) \right\}$$

that

$$\begin{aligned} \alpha^c(\omega) &= \Re(\alpha_*^c(\omega)) \approx a_1 |\omega|^\gamma = \alpha_*^{pl}(\omega), \\ \Im(\alpha_*^c(\omega)) &\approx -a_1 \tan\left(\gamma\frac{\pi}{2}\right) \text{sgn}(\omega) |\omega|^\gamma - a_2 \omega \end{aligned}$$

for $|\tau_0 \omega|^{\gamma-1} \ll 1$. We see that $\alpha_*^{pl}(\omega)$ is a good approximation of $\alpha_*^c(\omega)$ for *sufficiently small* frequencies. For the case $\tau_0 = 10^{-6} \mu s$ (liquid), the small frequency range condition $|\tau_0 \omega|^{\gamma-1} \leq 0.1$ is visualized in Table 1.

Table 1. Visualization of small frequency range condition $|\tau_0 \omega|^{\gamma-1} \leq 0.1$ for $\tau_0 = 10^{-6} \mu s$.

γ	range	bound M
1.1	$ \omega \leq 10^{-4} MHz$	$10^{-4} MHz$
1.5	$ \omega \leq 10^{-4} MHz$	$10^{-4} MHz$
2.0	$ \omega \leq 10^{-5} MHz$	$10^{-5} MHz$

2.3 Two results on causality

In Kowar et al. (2012), it is proven that the speed c_F of the wave front of $G(\mathbf{x}, t)$ with α_*^c defined as in (6) satisfies $c_F \leq c_0$ and in Kowar (2010) it is proven that $c_F = c_0$. Moreover, it is shown that $G(\mathbf{x}, t)$ with α_*^{pl} defined as in (7) with $a_2 = 0$ has not a bounded wave front speed. The same result is true for $a_2 \neq 0$.

Loosely speaking, causality restricts the growth of $\alpha(\omega)$ and consequently $\omega \mapsto \hat{G}(\mathbf{x}, \omega)$ must not decrease too fast for fixed $x \in \mathbb{R}^3 \setminus \{0\}$. If $\omega \mapsto \hat{G}(\mathbf{x}, \omega)$ decreases too fast, then it behaves like the truncated Green function

$$\hat{G}_M(\mathbf{x}, \omega) := \hat{G}(\mathbf{x}, \omega) \chi_{[-M, M]}(\omega), \quad (9)$$

for which causality condition (5) cannot hold. Here

$$\chi_{[-M, M]}(\omega) := \begin{cases} 1 & \text{if } \omega \in [-M, M] \\ 0 & \text{otherwise} \end{cases} \quad (10)$$

denotes the *characteristic function* of ω on $[-M, M]$.

3. SMALL FREQUENCY APPROXIMATION

We now derive two theorems that permit to estimate the quality of small frequency approximations. Let

- $G^c(\mathbf{x}, t)$ denote the Green function with α_*^c defined as in (6),

- $G^{pl}(\mathbf{x}, t)$ denote the Green function with α_*^{pl} defined as in (7),
- $\hat{G}_M(\mathbf{x}, \omega)$ be defined as in (9) and
- $G_M(\mathbf{x}, t) := \mathcal{F}^{-1}\{\hat{G}_M\}(\mathbf{x}, t)$.

Theorem 1. Let $M > 0$ and $A_0, A_1, A_3 > 0$ be such that

$$\alpha(M) + A_0 |\omega - M| \leq \alpha^c(\omega) \leq A_1 \omega^2 + A_2 |\omega| \quad (11)$$

holds for $|\omega| > M$. For $|\mathbf{x}| \neq 0$ it follows that

$$\frac{\|G^c(\mathbf{x}, \cdot) - G_M^c(\mathbf{x}, \cdot)\|_{L^2}}{\|G^c(\mathbf{x}, \cdot)\|_{L^2}} \leq \sqrt[4]{\frac{2 A_1}{\pi A_0^2}} \frac{e^{-\left(\alpha(M) + \frac{A_2^2}{4 A_1}\right) |\mathbf{x}|}}{\sqrt[4]{|\mathbf{x}|}}.$$

Proof. $\omega \mapsto \hat{G}^c(\mathbf{x}, \omega)$ and $\omega \mapsto \hat{G}_M^c(\mathbf{x}, \omega)$ are square integrable and thus their inverse Fourier transforms $t \mapsto G^c(\mathbf{x}, t)$ and $t \mapsto G_M^c(\mathbf{x}, t)$ are square integrable, too. Because of the *Plancherel-Parseval equality*, it follows

$$\frac{\|G^c(\mathbf{x}, \cdot) - G_M^c(\mathbf{x}, \cdot)\|_{L^2}}{\|G^c(\mathbf{x}, \cdot)\|_{L^2}} = \frac{\|\hat{G}^c(\mathbf{x}, \cdot) - \hat{G}_M^c(\mathbf{x}, \cdot)\|_{L^2}}{\|\hat{G}^c(\mathbf{x}, \cdot)\|_{L^2}}. \quad (12)$$

From (11) and

$$\int_{-\infty}^{\infty} \exp\{-\omega^2/2\} d\omega = \sqrt{2\pi},$$

it follows

$$\begin{aligned} \|\hat{G}^c(\mathbf{x}, \cdot) - \hat{G}_M^c(\mathbf{x}, \cdot)\|_{L^2}^2 &\leq 2 e^{-2\alpha(M)|\mathbf{x}|} \int_{-\infty}^{\infty} \frac{e^{-2A_0(\omega-M)|\mathbf{x}|}}{(4\pi|\mathbf{x}|)^2} d\omega \\ &\leq \frac{e^{-2\alpha(M)|\mathbf{x}|}}{(4\pi|\mathbf{x}|)^2 A_0 |\mathbf{x}|} \end{aligned}$$

and

$$\begin{aligned} \|\hat{G}^c(\mathbf{x}, \cdot)\|_{L^2}^2 &\geq \int_{-\infty}^{\infty} \frac{e^{-2(A_2|\omega| + A_1\omega^2)|\mathbf{x}|}}{(4\pi|\mathbf{x}|)^2} d\omega \\ &= \frac{\sqrt{\pi} e^{\frac{A_2^2|\mathbf{x}|}{2A_1}}}{(4\pi|\mathbf{x}|)^2 \sqrt{2A_1|\mathbf{x}|}} \end{aligned}$$

The theorem follows from (12) and the last two results.

Remark. Because $\omega \mapsto \hat{G}_M^c(\mathbf{x}, \omega)$ vanishes on a non-empty interval, causality condition (5) is not satisfied for G_M^c . However, Theorem 1 shows that $G_M^c(\mathbf{x}, t)$ is a good L^2 -approximation of $G^c(\mathbf{x}, t)$ if M is sufficiently large.

Theorem 2. Let $B_1 := \Re(\alpha_*^{pl} - \alpha_*^c)$, $B_2 := \Im(\alpha_*^{pl} - \alpha_*^c)$,

$$C := \left| 1 - 2 e^{-B_1(\omega)|\mathbf{x}|} \cos(B_2(\omega)|\mathbf{x}|) + e^{-2B_1(\omega)|\mathbf{x}|} \right|.$$

and $M_\delta \in (0, M]$ be such that

$$\|\hat{G}_{M_\delta}^c(\mathbf{x}, \omega)\|_{L^2}^2 = (1 - \delta) \|\hat{G}^c(\mathbf{x}, \omega)\|_{L^2}^2 \quad (13)$$

for some $0 < \delta \ll 1$. For $|\mathbf{x}| \neq 0$ it follows that

$$\frac{\|G_M^c(\mathbf{x}, \cdot) - G_M^{pl}(\mathbf{x}, \cdot)\|_{L^2}}{\|G^c(\mathbf{x}, \cdot)\|_{L^2}} \leq \sqrt{(1 - \delta) D_1(|\mathbf{x}|) + \delta D_2(|\mathbf{x}|)}$$

with $D_j(|\mathbf{x}|) := \max_{\omega \in I_j} C(|\mathbf{x}|, \omega)^2$ for $I_1 := [-M_\delta, M_\delta]$ and $I_2 := \mathbb{R} \setminus I_1$.

Proof. As in the proof of Theorem 1, it follows that

$$\frac{\|G_M^c(\mathbf{x}, \cdot) - G_M^{pl}(\mathbf{x}, \cdot)\|_{L^2}}{\|G_M^c(\mathbf{x}, \cdot)\|_{L^2}} = \frac{\|\hat{G}_M^c(\mathbf{x}, \cdot) - \hat{G}_M^{pl}(\mathbf{x}, \cdot)\|_{L^2}}{\|\hat{G}_M^c(\mathbf{x}, \cdot)\|_{L^2}}.$$

The theorem follows from the last result, (13) and

$$\begin{aligned} & \int |\hat{G}_M^c(\mathbf{x}, \cdot) - \hat{G}_M^{pl}(\mathbf{x}, \cdot)|^2 d\omega \\ & \leq D_1(|\mathbf{x}|) \int_{|\omega| \leq M_\delta} |\hat{G}_M^c(\mathbf{x}, \cdot)|^2 d\omega \\ & \quad + D_2(|\mathbf{x}|) \int_{|\omega| \geq M_\delta} |\hat{G}_M^c(\mathbf{x}, \cdot)|^2 d\omega. \end{aligned}$$

Cf. Fig. 3 from the example in Section 4 for which $\delta \approx 6 \cdot 10^{-4}$, $M_\delta \approx 10 \text{ MHz}$, $D_1(|\mathbf{x}|) \approx 5.6 \cdot 10^{-13}$ and $D_2(|\mathbf{x}|) \approx 1.04$, i.e. $\sqrt{(1-\delta) D_1(|\mathbf{x}|) + \delta D_2(|\mathbf{x}|)} = 0.025$.

4. NUMERICAL EXAMPLE

We now present a numerical example. We choose the following parameter values

$$\gamma \approx 1.66, \quad c_0 \approx 0.15 \frac{\text{cm}}{\mu\text{s}}, \quad \tau_0 \approx 10^{-6} \mu\text{s},$$

$$\alpha_1 = \frac{2 c_0 a_1}{\tau_0^{\gamma-1} |\cos(\gamma \pi/2)|} \approx 138.08 \text{ MHz}$$

(where we have used (8) and $a_1 \approx 0.04344 \frac{1}{\text{cm}}$) and

$$a_2 = \frac{\alpha_1}{c_0} \approx 920.55 \frac{1}{\text{cm}}$$

to model a medium similar to *castor oil*. (For the relaxation time τ_0 see Kinsler et al. (2000) and for a_1 and γ see Szabo (1995)).

The differences of the attenuation laws and the phase speeds of the attenuation-dispersion laws α_*^c and α_*^{pl} are visualized in Fig. 1. From the figure we see that α_*^{pl} is a good approximation of the attenuation-dispersion law α_*^c for the (practically measurable) frequency range $[0, 60] \text{ MHz}$. In the following we choose as small frequency bound:

$$M = 100 \text{ MHz} \ll \frac{1}{\tau_0}.$$

Small frequency approximation of causal model. For the estimation in Theorem 1 we choose the following constants

$$A_0 = 0.7 \frac{d\alpha^{pl}}{d\omega}(M), \quad A_1 = a_1 \quad \text{and} \quad A_2 = a_2$$

and obtain

$$\frac{\|G^c(\mathbf{x}, \cdot) - G_M^c(\mathbf{x}, \cdot)\|_{L^2}}{\|G^c(\mathbf{x}, \cdot)\|_{L^2}} \leq 0.0828 \frac{e^{-4.877 \cdot 10^6 \cdot |\mathbf{x}|}}{\sqrt[4]{|\mathbf{x}|}}.$$

Therefore the frequency range $[-10^2, 10^2]$ is reasonable for a small frequency approximation of G^c for distances larger than 10^{-6} cm .

Small frequency approximation via power law. In Fig. 3 we have visualized the functions $M_0 \mapsto g(M_0) := \|G_{M_0}^c(\mathbf{x}, \cdot)\|_{L^2}$ and $\omega \mapsto C(|\mathbf{x}|, \omega)$ for $|\mathbf{x}| = 1 \text{ cm}$. According to this figure and Theorem 2, G_M^{pl} is a good L^2 -approximation of G^c for the case $|\mathbf{x}| = 1 \text{ cm}$. In Table 2 we have listed the relative error

$$\epsilon_M(|\mathbf{x}|) := \frac{\|G_M^c(\mathbf{x}, \cdot) - G_M^{pl}(\mathbf{x}, \cdot)\|_{L^2}}{\|G_M^c(\mathbf{x}, \cdot)\|_{L^2}},$$

for different distances L . We see that $G_M^c(\mathbf{x}, t)$ and

Table 2. Visualization of error ϵ_M for different distances L (in cm).

L	10^{-6}	10^{-3}	10^{-1}	10
ϵ_M	$7.62 \cdot 10^{-8}$	$7.35 \cdot 10^{-5}$	$4.46 \cdot 10^{-4}$	$7.13 \cdot 10^{-5}$

$G_M^{pl}(\mathbf{x}, t)$ are good approximations of $G^c(\mathbf{x}, \cdot)$ as long as

$$M \geq 100 \text{ MHz} \quad \text{and} \quad |\mathbf{x}| \geq 10^{-6} \text{ cm}.$$

In particular, this means that the wave can be predicted for

$$t \geq \frac{10^{-6} \text{ cm}}{c_0} = 6.67 \cdot 10^{-6} \mu\text{s}.$$

Remark on causality. Because the wave G^c has the finite wave front speed $c_F = c_0$ and $G_M^{pl}(\mathbf{x}, \cdot)$ is a good L^2 -approximation of $G^c(\mathbf{x}, \cdot)$, it follows that G_M^{pl} has in “some sense” the same wave front speed. In “some sense” means that G_M^{pl} contains partial waves propagating arbitrarily fast but their sum is small in the L^2 -sense.

Remark on large frequencies. We note that the power attenuation law $\alpha^{pl}(\omega)$ increases much faster than $\alpha^c(\omega)$ for large frequencies and that the respective phase speed $c^{pl}(\omega)$ has a singularity at $\omega_1 \approx 7.950959 \cdot 10^6 \text{ MHz}$ and at $\omega_2 = -\omega_1$ (cf. Fig 2), respectively. In contrast to the latter fact, the phase speed $c^c(\omega)$ of the causal model has no singularity.

5. CONCLUSIONS

We showed that - for appropriate situations - the causal wave G^c defined by (2), (3) and (6) can be approximated by the noncausal wave G_M^{pl} defined by (9) (2), (3), (7) and (8). In words, the wave G^{pl} contains partial waves propagating arbitrarily fast but the sum of the noncausal waves is small in the L^2 -sense. This result fits in with the results in Kelly et al. (2008).

REFERENCES

- Chen, W and Holm, S.: Fractional Laplacian time-space models for linear and nonlinear lossy media exhibiting arbitrary frequency power-law dependency. *J. Acoust. Soc. Am.* 115 (4), April 2004.
- Kinsler, L. E., Frey, A. R., Coppens, A. B. and Sanders, J. V. (2000). *Fundamentals of Acoustics*. Wiley, New York, 2000.
- Kowar, R., Scherzer, O. and Bonnefond, X. (2011). Causality analysis of frequency dependent wave attenuation. *Math. Appl. Sci.* 34 108-124, 2011.
- Kowar, R. (2010). On causality of Thermoacoustic tomography of dissipative tissue. *Conference Proceedings ECMI 2010*, (6 pages).
- Kowar, R. and Scherzer, O. (2012). Attenuation Models in Photoacoustics. to appear in: *Mathematical Modeling in Biomedical Imaging II Lecture Notes in Mathematics*, 2012, Volume 2035/2012, 85-130. (arXiv:1009.4350)
- Kelley, J.F., McGough, R.J. and Meerschaert, M.M (2008). Analytical time-domain Green's function for power-law media. *J. Acoust. Soc. Amer.*, 124(5): 28612872, 2008.

Nachman, A. I. and Smith, J. F., III and Waag, R. C.: An equation for acoustic propagation in inhomogeneous media with relaxation losses. *J. Acoust. Soc. Am.* 88 (3), Sept. 1990.

Patch, S. K. and Greenleaf, A.: Equations governing waves with attenuation according to power law. *Technical report*, Department of Physics, University of Wisconsin-Milwaukee, 2006.

Szabo, T.L. (1995). Causal theories and data for acoustic attenuation obeying a frequency power law. *J. Acoust. Soc. Amer.*, 97:14–24, 1995.

Waters, K. R., Hughes, M. S., Brandenburger, G. H. and Miller, J. G. (2000). On a time-domain representation of the Kramers-Krönig dispersion relation. *J. Acoust. Soc. Amer.*, 108(5):2114–2119, 2000.




Fig. 1. Numerical comparison of the attenuation laws and phase speeds. The dashed lines correspond to model $\alpha_*^c(\omega)$ and the solid lines correspond to model $\alpha_*^{pl}(\omega)$.




Fig. 2. Numerical comparison of the attenuation laws and phase speeds for large frequencies The dashed lines correspond to model $\alpha_*^c(\omega)$ and the solid lines correspond to model $\alpha_*^{pl}(\omega)$.




Fig. 3. Visualization of functions $M_0 \mapsto g(M_0) := \|G_{M_0}^c(\mathbf{x}, \cdot)\|_{L^2}$ and $\omega \mapsto C(|\mathbf{x}|, \omega)$ for $|\mathbf{x}| = 1$ cm.